



PROSCREEN™ PS101

PROFESSIONAL POP FILTER WITH GOOSENECK

SETUP: The Proscreen™ PS101 features a long, rigid gooseneck and adjustable clamp, providing easy setup with any professional mic stand. The photograph below represents a typical setup.

USE: For best results the PS101 should be placed between the vocalist and the microphone with at least two inches between the screen and the microphone.

Important note: proper orientation of the screen to the microphone is critical. The vocalist must be facing the Stedman label side of the Proscreen™ PS101 for the screen to be effective.



CLEANING: To wash the Proscreen™ PS101, immerse the entire perforated screen into a mild solution of detergent and rinse with warm water. Wipe off excess water with a towel and allow to air dry before the next use. An antibacterial detergent may be used to increase effectiveness of cleaning.

THE WORLD'S MOST EFFECTIVE POP FILTERS!

NEW!

PureConnect™ CONNECTOR CLEANER KITS



1/4" diameter microfelt tip cleans both guitar jacks and XLR connector pins



1/10" diameter microfelt tips clean XLR female terminals



Lifetime handle holds both microfelt felt tip sizes

1 3/4" cotton pads for cleaning 1/4" male plugs



2 ml DeoxiT cleaning fluid for use on tips and pads to clean connectors

MULTIPLE KIT SIZES AVAILABLE. PLEASE VISIT: STEDMANUSA.COM

ALL STEDMAN PRODUCTS INCLUDE
A LIFETIME WARRANTY

STEDMAN®

STEDMAN CORPORATION
9625 East D Ave
Richland, MI 49083 USA
888-629-5960 toll free
269-629-5930 phone
www.stedmanusa.com



MADE IN U.S.A.

